Wireless Lavalier Microphone

User Manual



MADE IN CHINA


Product Introduction

Thank you very much for choosing our products. This product is an intelligent wireless lavalier microphone, which can provide professional-level recording and live broadcast output, plug and play, no App required. Wide range of uses: It can be used in web live broadcast, video VLOG shooting, program interviews, interview recordings, video teaching and other scenarios.
This product consists of three parts, the microphone, the receiver and the charging case. As shown in the figure below (some models do not have a charging case, the actual product shall prevail):



Charging case　Microphone　Receiver


Function Description



① Power on/off button
② Noise reduction button
③ Pickup microphone
④ Microphone clip
⑤ Charging and monitoring headphone interface
⑥ Connection and charging indicator light
⑦ Noise reduction indicator light
⑧ Reverb indicator light
⑨ Microphone off indicator light
⑩ Volume switch button
⑪ Connection indicator light
⑫ Volume indicator light
⑬ Charging interface
⑭ Charging case power display

Usage Method

Step 1: Connect the receiver to the mobile phone interface.




Note: OPPO / VIVO / iQOO / Realme and brand mobile phones that cannot be connected can be used normally in the mobile phone settings (search for "OTG" and turn on the OTG power supply).

Usage Method

Step 2: Take the microphone out of the charging case, and the connection indicator light will be on for a long time to use the microphone to receive audio.





Special Notes

Usage method of the charging interface on the receiver: In case the power of your mobile phone is insufficient when shooting short videos or doing live broadcasts, you can charge the mobile phone through the interface on the receiver.



UI Functions

Microphone

Function/Status	Button/Operations	Lighting effect
Turn on	Take out the charging case and turn it on (or press the power button for 3s to turn it on)	The blue light of the connection indicator is flashing
Turn off	Put it into the charging case and turn it off (or press the power button for 3s to turn off)	All lights off
Not connected	——	Blue light flashing
Connected	——	Blue light is always on
Noise reduction	Push the noise reduction button downward (Pull the noise reduction upward to restore)	Noise Cancellation indicator on
Reverb	Click the power button (click restore again)	Reverb indicator on
Mute	Double-click the power key to mute (double-click again to restore sound)	Mute indicator on
Charge	Put in the charging case or plug in the charging cable	Green light is always on
Fully Charged	——	Green light off
Low battery	——	Red light flashing

UI Functions

Receiver

Function/Status	Button/Operations	Lighting effect
Turn on	Plug in the device and power on	Blue light flashing
Turn off	Unplug the device and power off	Blue light off
Not connected	——	Blue light flashing
Connected	——	Blue light is always on
Adjust volume	Single-click	Increase or decrease the number of blue lights
Voice Changer (Child Voice)	Double-click	First blue light flashes
Voice Changer (Male Voice)	Double-click	Second blue light flashes
Voice Changer (Female Voice)	Double-click	Third blue light flashes
Stereo Sound	Triple-click	Blue lights flash in sequence

UI Functions

Charging case

Function/Status	Button/Operations	Lighting effect
Charge	Insert the charging cable	The single digit on the display flashes
Fully charged	——	The display is 100% always on
Low battery	——	When the battery is 5%, the single digit flashes slowly
Discharge	——	Always on to display real-time power

Product Parameters

Headphone monitoring	The microphone can monitor at the same time (adapted to TYPE-C analog Interface headphones)
Sound delay	≤20ms
Microphone	–36dB omnidirectional
Frequency response	20Hz-20kHz
Sampling rate	44.1kHz (32kHz noise reduction)
Signal-to-Noise Ratio	68dB
Working current	≤12mA
Single microphone battery life	9 hours
Battery life with dual microphones at the same time	With the charging case, the longest battery life is more than 25 hours
Microphone battery	110mAh
Case battery	300mAh
Case battery life	Can charge two microphones 2.7 times at the same time
Case input voltage	DC4.5–5.2V (support fast charging adapter)
Adapter	5V/1A
Operating temperature	-10℃-50℃
Dimensions (mm)	Microphone: 46×17×16 /Receiver: 34.5×22×8.5 Charging case: 54×54×21
Weight	Microphone: 10g Receiver: 5g Charging case: 38g

65.00 mm

71.05 mm

БЕСПРОВОДНОЙ ПЕТЛИЧНЫЙ МИКРОФОН

Руководство пользователя



MADE IN CHINA

Представление изделия

Спасибо за выбор нашей продукции. Этот продукт представляет собой интеллектуальный беспроводной петличный микрофон, который может обеспечивать запись профессионального уровня и вывод в прямую трансляцию, функция подключи и используй, приложение не требуется. Широкий спектр применения: Его можно использовать для веб трансляций, съемки видеоблогов, записи интервью, обучающих видео и других сценариях. Изделие состоит из трех частей: передатчика, приемника и зарядного кейса.



зарядный отсек　микрофон　приемник


Описание функций



① Кнопка включения и выключения
② Кнопка подавления шума
③ Микрофон
④ Клипса
⑤ Разъем для зарядки и наушников для мониторинга
⑥ Индикатор подключения и зарядки
⑦ Индикатор подавления шума
⑧ Индикатор реверберации
⑨ Индикатор выключения микрофона
⑩ Переключатель громкости
⑪ Индикатор подключения
⑫ Индикатор громкости
⑬ Зарядной разъем
⑭ Показание заряда

Способ использования

1.Вставьте приемник в мобильный телефон




Примечание: OPPO\VIVO\iQOO\Realme и другие бренды, которые не работают сразу, необходимо включить функцию OTG в настройках вашего устройства.

Способ использования

2.Извлеките передатчик из батарейного отсека. Когда индикатор подключения горадо постоянно, можно использовать микрофон для записи звука





Особое примечание

Если батарея мобильного устройства разряжается, необязательно прерывать запись, Вы можете зарядить устройство через порт зарядки на приемнике (ресивере).



функция

микрофон

Функция/Состояние	Кнопки/Операции	Эффекты подсветки
Включение	Достаньте из кейса и включите (или зажмите кнопку питания в течение 3 секунд)	Мигает синий индикатор подключения
Выключение	Положите в кейс и выключите (или зажмите кнопку питания в течение 3 секунд)	Свет погаснет
Не подключен	——	Мигающий синий
Подключен	——	Синий всегда горит
Шумоподавление	Переместите клавишу включения (функция шумоподавления вернется в свое положение)	Индикатор подавления шума горит
Реверберация	Короткое нажатие кнопки питания (еще раз для возврата)	Индикатор реверберации горит
Отключение звука	Двойное нажатие кнопки питания чтобы выключить (еще раз для возврата)	Индикатор выключения микрофона горит
Зарядка	Положите в зарядный кейс или подключите кабель зарядки	Зеленый всегда горит
Заряжен	——	Зеленый свет погаснет
Слабый заряд	——	Мигающий красный

функция

приемник

Функция/Состояние	Кнопки/Операции	Эффекты подсветки
Включение	Подключите к устройству	Мигающий синий
Выключение	Отключите от устройства	Синий свет погаснет
Не подключен	——	Мигающий синий
Подключен	——	Синий всегда горит
Регулировка громкости	Однократное нажатие	Увеличить или уменьшить количество синих индикаторов
Изменитель голоса (детский голос)	Двойное нажатие	Мигает первый синий индикатор
Изменитель голоса (мужской голос)	Двойное нажатие	Мигает второй синий индикатор
Изменитель голоса (женский голос)	Двойное нажатие	Мигает третий синий индикатор
Стереозвук	Тройное нажатие	Синие индикаторы мигают по очереди

функция

зарядный отсек

Функция/Состояние	Кнопки/Операции	Эффекты подсветки
Заряжать	Подсоедините зарядный кабель	Цифры будут мигать
Заряжен	——	Всегда горят 100%
Слабый заряд	——	Когда заряд 5%, цифры будут медленно мигать
Индикация заряда	——	Всегда включен для отображения оставшегося заряда

Характеристики продукта

Мониторинг гарнитуры	Передатчик поддерживает мониторинг (совместим с наушниками с аналоговым интерфейсом Type-C)
Задержка звука	≤20 мс
Микрофон	–36 дБ всенаправленный
Частотная характеристика	20 Гц - 20 кГц
Частота дискретизации	44.1 кГц (32 кГц с шумоподавлением)
Отношение сигнал/шум	68дБ
Рабочий ток	≤12мА
Время автономной работы одного микрофона	9 часов
Время автономной работы при использовании двух микрофонов	Более 25 часов с зарядным кейсом
Батарея микрофона	110мАч
Батарея зарядного кейса	300мАч
Ресурс зарядного кейса	Может зарядить один микрофон 2.7 раза
Входное напряжение	DC4.5-5.2 В (поддерживает быструю зарядку)
Адаптер питания	5 В/1 А
Рабочая температура	-10°C-50°C
Размеры (мм)	Передатчик: 46×17×16 /Приемник: 34.5×22×8.5 Зарядный кейс: 54×56×21
Вес	Передатчик: 10 г /Приемник: 5 г /Зарядный кейс: 38 г