БЕСПРОВОДНОЙ ПЕТЛИЧНЫЙ МИКРОФОН

Руководство пользователя

СДЕЛАНО В КИТАЕ

Описание продукта


Спасибо за выбор нашей продукции. Этот продукт представляет собой интеллектуальный беспроводной петличный микрофон, который может обеспечивать запись профессионального уровня и вывод в прямую трансляцию, функция подключи и используй, приложение не требуется. Широкий спектр применения: Его можно использовать для веб трансляций, съемки видеоблогов, записи интервью, обучающих видео и других сценариях. Изделие состоит из трех частей: передатчика, приемника и зарядного кейса. Просим обратить внимание, что в модели с разъемом AUX зарядного кейса нет.




Зарядный кейс



Передатчик (микрофон)




Приемник (ресивер)



1. Кнопка вкл\выкл\пауза\смена режима записи
2. Шумоподавление
3. Микрофон
4. Клипса
5. Разъем для зарядки микрофона или подключения наушников
6. Индикатор подключения и зарядки
7. Индикатор шумоподавления
8. Индикатор режима реверберации(эхо)
9. Индикатор микрофона
10. Разъем подключения
11. Индикатор подключения
12. Разъем для зарядки подключенного устройства или подключения наушников
13. Разъем зарядки кейса
14. Индикация заряда


Инструкция по подключению

1. Подключите приемник (ресивер) в разъем подключаемого устройства



Примечание: OPPO\VIVO\IQOO\REALME и другие бренды, которые не работают сразу, необходимо включить функцию OTG в настройках вашего устройства.

2. Извлеките микрофон из зарядного кейса, индикатор подключения будет постоянно гореть, значит микрофон готов к работе.



Особое примечание

Если батарея мобильного устройства разряжается, необязательно прерывать запись, Вы можете зарядить устройство через порт зарядки на приемнике (ресивере).



Особенности

Передатчик (микрофон)

Функции/Статус	Клавиши/Операции	Световой эффект
Включение	Достаньте из кейса и включите (или зажмите кнопку питания в течение 3 секунд)	Мигающий синий
Выключение	Положите в кейс и выключите (или зажмите кнопку питания в течение 3 секунд)	Свет погаснет
Не подключен		Мигающий синий
Подключен		Синий всегда горит
Шумоподавление	Переместите клавишу включения (функция заработает, клавиша вернется в свое положение)	Индикатор шумоподавления
Переключение режима записи	Короткое нажатие кнопки питания (еще раз для возврата)	Индикатор режима
Отключение звука	Двойное нажатие кнопки питания чтобы выключить (еще раз для возврата)	Индикатор звука
Зарядка	Положите в зарядный кейс или подключите кабель зарядки	Зеленый всегда горит
Заряжен		Зеленый свет погаснет
Слабый заряд		Мигающий красный

Приемник (ресивер)

Функции/Статус	Операции	Световой эффект
Включение	Подключите к устройству	Мигающий синий
Выключение	Отключите от устройства	Синий свет погаснет
Не подключен		Мигающий синий
Подключен		Синий всегда горит

Зарядный кейс

Функции/Статус	Операции	Дисплей/Эффект
Кейс	Подсоедините зарядный кабель	Цифры будут мигать
Заряжен		Всегда горит 100%
Слабый заряд		Когда заряд 5%, цифры будут медленно мигать
Индикация заряда		Всегда включен для отображения оставшихся зарядов

Характеристики продукта

Мониторинг гарнитуры	Приемник и передатчик могут быть подключены в одно время (разъем Type-C)
Задержка звука	Интерфейсные наушники
Микрофон	≤ 35мс (18.25мс)
Частотная характеристика	3Н+2 дВ всенаправленный
Частота дискретизации	20Hz-20KHz440Hz (32KHz шумоподавление)
Отношение сигнал/шум	>70 дБ
Рабочий ток	<12 мА
Время автономной работы одного микрофона	9 часов
Время автономной работы при использовании двух микрофонов	С зарядным кейсом более 33 часов
Батарея микрофона	110 мА
Батарея зарядного кейса	600 мА
Ресурс батареи	Зарядит два микрофона 2.7 раз
Входное напряжение	DC4.5-5.2V (поддержка быстрой зарядки)
Адаптер	5V/1A
Рабочая температура	-10 °C ~ 50 °C
Размеры (мм)	Микрофон: 86x16x10, Приемник: 42x15x7.5, Кейс: 77x62x27
Вес	Микрофон: 10г, Приемник: 5г, Кейс: 55г

Комплектация

1. Передатчик (микрофон)
2. Приемник (ресивер)
3. Зарядный кейс (кроме модели с разъемом AUX)
4. Зарядный кабель Type-C
5. Руководство пользователя

Wireless Lavalier Microphone

User's manual

MADE IN CHINA

Product description


Thank you very much for choosing our products. This product is an intelligent wireless lavalier microphone, which can provide professional-level recording and live broadcast output, plug and play, no App required. Wide range of uses: It can be used in web live broadcast, video VLOG shooting, program interviews, interview recordings, video teaching and other scenarios. This product consists of three parts, the transmitter, the receiver and the charging compartment. As shown in the figure below (some models do not have a charging compartment, the actual product shall prevail):




Charging case



The transmitting end




Receiving end



①Switch key
②Noise reduction key
③Pickup microphone
④Microphone clip
⑤Charging and monitoring headphone jack
⑥Connection and charging indicator light
⑦Noise reduction indicator light
⑧Reverb indicator
⑨Mic off indicator light
⑩Mobile phone interface
⑪Connection indicator light
⑫Charging interface
⑬Charging interface
⑭Charging compartment power display


Instructions

Step 1: Connect the receiver to the mobile phone interface



Note: OPPO/VIVO/IQOO/REALME and brand mobile phones that cannot be connected can be used normally in the mobile phone settings (search for "OTG" and turn on the OTG power supply).

Step 2: Take the transmitter out of the battery compartment, and the connection indicator light will be on for a long time to use the microphone to receive audio.



Special note

How to use the charging interface on the receiving end: If the cell phone battery is insufficient when recording short videos or live broadcasts, you can charge the cell phone through the interface on the receiving end.



UI features

The transmitting end

Function/Status	Keys/Operations:	Lighting effect:
Boot	Take out the charging case and turn it on (or press the power button for 3S to turn it on).	Blue light flashing
Shutdown	Put it into the charging case and turn it off (or press the power button for 3S to turn off).	All lights off
Not connected		Blue light flashing
Connected		Blue light is always on
Noise reduction	Move the noise canceling key down (the noise canceling key will resume up)	Noise Cancellation indicator is on
Reverberation	Click the power button (click restore again)	Reverb indicator on
Mute off	Double-click the power button to turn off the microphone (double-click again to restore)	Mic off indicator is on
Mute on	Put in the charging case or plug in the charging cable	Green light is always on
Fully charged		Green light off
Low power		Flashing red

Receiving end

Function/Status	Operate:	Unplug the device and power off
Boot	Plug in the device and power on	Lighting effect: blue light flashing
Shutdown	Unplug the device and power off	Blue light off
Not connected		Blue light flashing
Connected		Blue light is always on

Charging case

Function/Status:	Operate:	Display/Lighting effect:
Charging case	Insert the charging cable	The single digit on the display flashes
The charging compartment is fully charged		The display is 100% always on
Low battery in charging compartment		When the battery is 5%, the single digit flashes slowly
Discharging the charging compartment		Always on to display real-time power

Product parameters

Headphone monitoring	The receiver and transmitter can monitor at the same time (adapted to TYPE-C analog
Sound delay	Interface headphones)
Microphone	<25ms(18-22ms)
Frequency response	3H+10DB omnidirectional
Sampling Rate	20Hz-20KHz44.1KHz (32KHz noise reduction)
Signal to noise ratio	>70dB
Working current	<12mA
Standby time (Microphone)	9 hours
Battery life with dual microphones at the same time	With the charging case, the longest battery life is more than 33 hours
Microphone battery	110 mA
Charging compartment battery	600 mA
Battery life	Can charge two microphones 2.7 times at the same time
Charging compartment input voltage	DC4.5-5.2V (support fast charging adapter)
Adapter	5V/1A
Operating temperature	-10℃-50℃
Dimensions (mm)	Transmitter: 46×16x10 Receiver: 42x 15x7.5 Charger: 77x62 x 27 mumb.
Weight	Transmitter: 10g Receiver: 5g Charging compartment: 55g

Packing list

1. Microphone transmitter
2. Receiver
3. Charging compartment (some models do not have a charging compartment, the actual product shall prevail)
4. TYPE-C charging cable
5. User Manual